

HEX DIGITS 1ST → 2ND ↓	0-	1-	2-	3-	4-	5-	6-	7-	8-	9-	A-	B-	C-	D-	E-	F-
-0			(SP) SP010000	0 ND100000	@ SM050000	P LP020000	` SD130000	p LP010000	€ SP200000		(RSP) SP300000	° SM190000	♀ SD808000	∣ SD650000	א HX330000	נ HN010000
-1			! SP020000	1 ND010000	A LA020000	Q LQ020000	a LA010000	q LQ010000		‘ SP190000		± SA020000	♀ SD818000	◌̇ SD968000	ב HB010000	ס HS010000
-2			" SP040000	2 ND020000	B LB020000	R LR020000	b LB010000	r LR010000	, SP260000	, SP200000	¢ SC040000	2 ND021000	♀ SD828000	◌̇ SD978000	ג HG010000	ע HX350000
-3			# SM010000	3 ND030000	C LC020000	S LS020000	c LC010000	s LS010000	f SC070000	“ SP210000	£ SC020000	3 ND031000	♀ SD838000	: SD660000	ד HD010000	ך HP610000
-4			\$ SC030000	4 ND040000	D LD020000	T LT020000	d LD010000	t LT010000	„ SP230000	” SP220000	₪ SC170000	’ SD110000	♀ SD848000	ן HW610000	ה HH010000	פ HP010000
-5			% SM020000	5 ND050000	E LE020000	U LU020000	e LE010000	u LU010000	... SV520000	● SM570000	¥ SC050000	μ SM170000	♀ SD858000	ו HW630000	ו HW010000	ץ HS610000
-6			& SM030000	6 ND060000	F LF020000	V LV020000	f LF010000	v LV010000	† SM340000	- SS680000	∣ SM650000	¶ SM250000	♀ SD868000	” HY610000	ז HZ010000	צ HS450000
-7			’ SP050000	7 ND070000	G LG020000	W LW020000	g LG010000	w LW010000	‡ SM350000	— SM900000	§ SM240000	• SD630000	♀ SD878000		ח HH450000	ק HQ010000
-8			(SP060000	8 ND080000	H LH020000	X LX020000	h LH010000	x LX010000	^ SD150100	~ SD190100	.. SD170000		♀ SD888000		ט HT450000	ך HR010000
-9) SP070000	9 ND090000	I LI020000	Y LY020000	i LI010000	y LY010000	‰ SM560000	™ SM540000	© SM520000	1 ND011000	◌̇ SD898000		י HY010000	ש HS210000
-A			* SM040000	: SP130000	J LJ020000	Z LZ020000	j LJ010000	z LZ010000							ך HK610000	ת HT010000
-B			+ SA010000	; SP140000	K LK020000	[SM060000	k LK010000	{ SM110000	< SP270000	> SP280000	« SP170000	» SP180000	♀ SD928000		כ HK010000	
-C			, SP080000	< SA030000	L LL020000	\ SM070000	l LL010000	 SM130000			⌋ SM660000	¼ NF040000	◌̇ SD938000		ל HL010000	
-D			- SP100000	= SA040000	M LM020000] SM080000	m LM010000	} SM140000			(SHY) SP320000	½ NF010000	◌̇ SD948000		ם HM610000	(LRM) SP5500Z0
-E			. SP110000	> SA050000	N LN020000	^ SD150000	n LN010000	~ SD190000			® SM530000	¾ NF050000	◌̇ SD640000		נ HM010000	(RLM) SP5600Z0
-F			/ SP120000	? SP150000	O LO020000	_ SP090000	o LO010000				- SD310000		◌̇ SD958000		ן HN610000	